DL-SE 06-130/T-EN54

Ceiling speaker for Voice Alarm, 6W power, certified EN 54-24



Technical Data

Colour	RAL 9016
Dimensions	180x100 mm
Ceiling Cut-out	155 mm
Dispersion -6dB, 500Hz	180° h/v
Dispersion -6dB, 1KHz	180° h/v
Dispersion -6dB, 2KHz	150° h/v
Dispersion -6dB, 4KHz	75° h/v
Frequency Range	80 - 20.000 Hz
Frequency Response	64 - 21.500 Hz
Power	6/3/1,5 W

TO MAKE PEOPLE LISTEN

Copyright ©2026 ic audio GmbH. All rights reserved. Date: 2026-10-07

DL-SE 06-130/T-EN54

Mounting Instruction

1. Create the necessary ceiling cut-out and check the installation depth.
2. Loosen the screws of the terminal cover, slide it to the right and remove the cover.
3. Guide the speaker cable through the cable gland of the terminal cover.
4. Connect the speaker cables to the WAGO terminal.
5. Put the terminal cover back on the rear of the speaker and slide the cover to the left. Tighten the screws again.
6. Fold up the speaker's leg springs and insert the speaker into the ceiling cut-out until it is flush with the ceiling.

Power Tappings

Black	Red	White	Green
COM	6	3	1,5

CE
19

CE-Symbol according to 93/68EWG
Measurements according to DIN IEC 268-5
RoHS compliant (2011/65/EU)
CPR compliance according 305/2011/EU

Loudspeaker for voice alarm systems for fire detection and fire alarm systems for buildings
ic audio GmbH, Boehringerstraße 14A
68307 Mannheim, Germany

EN54-24:2008
Ref. Nr.:001-18
ID-Code:SAA-1801
1438-CPR-0642

TO MAKE PEOPLE LISTEN

Copyright ©2026 ic audio GmbH. All rights reserved. Date: 2026-10-07