WA 10-165/T Metal-EN54

Wall speaker for Voice Alarm, 10W power, certified EN 54-24



Mechanical Data

Colour	RAL 9010
Dimensions	252x192x83 mm
Weight (net)	2,71 kg
Power	10/6/3/1,5 W
Connector	2-pin ceramic block
Terminal Diameter	3,2 mm
Maximum Cable Passage	8 mm^2
Mounting	Screws

TO MAKE PEOPLE LISTEN

Copyright ©2026 ic audio GmbH. All rights reserved. Date: 2026-10-26


WA 10-165/T METAL-EN54

4 260590 181787

Mounting Instruction

1. Attach the back panel of the speaker to the wall. Use the enclosed screws.
2. Feed the connection cable through the cut-out in the rear wall of the speaker or use the inputs on the side or top/bottom by knocking out the pre-punched holes and fitting them with the enclosed rubber grommets.
3. Connect the power cable to the ceramic terminal (COM and 100V). If necessary, select a different power tapping on the transformer.
4. Connect the red/black plug-in cable of the transformer to the loudspeaker.
5. Place the loudspeaker housing on the wall-mounted rear wall of the loudspeaker.
6. Use the 3 enclosed screws incl. spring washers to fasten the loudspeaker.

Please note: To avoid damage, we recommend loosening the cable lug with a flat-blade screwdriver when changing the cable to a different power tapping.



CE
19

CE-Symbol according to 93/68EWG
Measurements according to DIN IEC 268-5
RoHS compliant (2011/65/EU)
CPR compliance according 305/2011/EU

Loudspeaker for voice alarm systems for fire detection and fire alarm systems for buildings
ic audio GmbH, Boehringerstraße 14A
68307 Mannheim, Germany

EN54-24:2008
Ref. Nr.:007-13
ID-Code:SAA-LS07
1438-CPR-0231

TO MAKE PEOPLE LISTEN

Copyright ©2026 ic audio GmbH. All rights reserved. Date: 2026-10-26