



DL-SE 06-130/T-EN54-C

Ceiling speaker for Voice Alarm, 6W power, certified EN 54-24

Technical Data

Colour	RAL 9016
Dimensions	180x93 mm
Ceiling Cut-out	161-167 mm
Dispersion -6dB, 500Hz	180° h/v
Dispersion -6dB, 1KHz	180° h/v
Dispersion -6dB, 2KHz	150° h/v
Dispersion -6dB, 4KHz	75° h/v
Sensitivity EN54-24, 1W/1m	90,0 dB
Sensitivity EN54-24, 1W/4m	78,0 dB
Frequency Range	80 - 20.000 Hz
Frequency Response	64 - 21.500 Hz
SPL IEC268-5, 1W/1m	90,0 dB
SPL EN54-24, Pmax/4m	85,0 dB
Power	6/3/1,5 W



DL-SE 06-130/T-EN54-C

Mounting Instruction

- 1. Create the necessary ceiling cut-out and check the installation depth.
- 2. Loosen the screws of the terminal cover, slide it to the right and remove the cover.
- 3. Guide the speaker cable through the cable gland of the terminal cover.
- 4. Connect the speaker cables to the WAGO terminal.
- 5. Put the terminal cover back on the rear of the speaker and slide the cover to the left. Tighten the screws again.
- 6. Fold up the speaker's leg springs and insert the speaker into the ceiling cut-out until it is flush with the ceiling.

Power Tappings

Black	Red	White	Green
COM	6	3	1,5

TO MAKE PEOPLE LISTEN



CE-Symbol according to 93/68EWG
Measurements according to DIN IEC 268-5
RoHS compliant (2011/65/EU)
CPR compliance according 305/2011/EU

Loudspeaker for voice alarm systems for fire
detection and fire alarm systems for buildings
ic audio GmbH, Boehringerstraße 14A
68307 Mannheim, Germany

EN54-24:2008
Ref. Nr.:001-18
ID-Code:SAA-1801
1438-CPR-0642