

DL-SE 06-165/T-EN54 SAFE STR

Ceiling speaker for voice alarm, 6W power, EN 54-24 certified



Technical Data

Colour	RAL 9016
Dimensions	220x104 mm
Ceiling Cut-out	188 mm
Dispersion -6dB, 500Hz	180° h/v
Dispersion -6dB, 1KHz	175° h/v
Dispersion -6dB, 2KHz	150° h/v
Dispersion -6dB, 4KHz	90° h/v
Sensitivity EN54-24, 1W/1m	92,0 dB
Sensitivity EN54-24, 1W/4m	80,0 dB
Frequency Range	63 ~ 16000 Hz
Frequency Response	56 ~ 18000 Hz
SPL IEC268-5, 1W/1m	92,0 dB
SPL EN54-24, Pmax/4m	87,0 dB
Power	6/3/1,5 W



DL-SE 06-165/T-EN54 SAFE STR

Mounting Instruction

1. Create the necessary ceiling cut-out and check the installation depth.
2. Loosen the screws of the terminal cover, slide it to the right and remove the cover.
3. Guide the speaker cable through the cable gland of the terminal cover.
4. Connect the power cable to the ceramic terminal (COM and 100V).
5. Connect the connection cable for the strobe light to the ceramic terminal (24V).
6. Put the terminal cover back on the rear of the speaker and slide the cover to the left. Tighten the screws again.
7. Fold the speaker's leaf springs upwards and insert the speaker into the ceiling cut-out until it is flush with the ceiling.



CE-Symbol according to 93/68EWG
Measurements according to DIN IEC 268-5
RoHS compliant (2011/65/EU)
CPR compliance according 305/2011/EU

Loudspeaker for voice alarm systems for fire detection and fire alarm systems for buildings : EN54-24:2008
ic audio GmbH, Boehringerstraße 14A :
68307 Mannheim, Germany

TO MAKE PEOPLE LISTEN