

DL-SE-AB 06-200/T-EN54

Ceiling speaker for Voice Alarm, A/B-cabling, 2x6 power, certified EN 54-24



Technical Data

Colour	RAL 9016
Dimensions	265x85 mm
Ceiling Cut-out	245 mm
Dispersion -6dB, 500Hz	180° h/v (s/d)
Dispersion -6dB, 1KHz	180° h/v (s/d)
Dispersion -6dB, 2KHz	180° h/v (single) 84°/187° h/v (double)
Dispersion -6dB, 4KHz	134°/98° h/v (single) 41°/97° h/v (double)
Sensitivity EN54-24, 1W/1m	85,0 dB (single) 87,7 dB (double)
Sensitivity EN54-24, 1W/4m	73,0 dB (single) 75,7 dB (double)
Frequency Range	90 ~ 17.000 Hz (single) 100 ~ 19.500 Hz (double)
Frequency Response	80 ~ 20.000 Hz (single) 90 ~ 20.500 Hz (double)
SPL IEC268-5, 1W/1m	86,0 dB 90,0 dB (double)
SPL EN54-24, Pmax/4m	80,6 dB (single) 86,3 dB (double)
Power	2x 6/3 /1.5 W



DL-SE-AB 06-200/T-EN54

Mounting Instruction

1. Create the necessary ceiling cut-out and check the installation depth.
2. Loosen the screws of the terminal cover, slide it to the right and remove the cover.
3. Guide the speaker cable through the cable gland of the terminal cover.
4. Connect the speaker cables to the WAGO terminal.
5. Put the terminal cover back on the rear of the speaker and slide the cover to the left. Tighten the screws again.
6. Fold up the speaker's leg springs and insert the speaker into the ceiling cut-out until it is flush with the ceiling.

Power Tappings

Black	Red	White	Green
COM	6W	3W	1,5



CE-Symbol according to 93/68EWG
Measurements according to DIN IEC 268-5
RoHS compliant (2011/65/EU)
CPR compliance according 305/2011/EU

Loudspeaker for voice alarm systems for fire
detection and fire alarm systems for buildings
ic audio GmbH, Boehringerstraße 14A
D-68307 Mannheim, Germany

EN54-24:2008
Ref. Nr.:001-35
ID-Code:SAA-LS35
1438-CPR-0642