

## PRO 60-130T/ PLUS WHITE-EN54

2-way coaxial speaker for Voice Alarm, 60W power, certified EN 54-24



### Technical Data

Colour	RAL 9016
Dimensions	180x180x194 mm
Dispersion -6dB, 500Hz	360° (h) 360° (v)
Dispersion -6dB, 1KHz	140° (h) 154° (v)
Dispersion -6dB, 2KHz	87° (h) 87° (v)
Dispersion -6dB, 4KHz	103° (h) 94° (v)
Sensitivity EN54-24, 1W/1m	88,4 dB
Sensitivity EN54-24, 1W/4m	76,4 dB
Frequency Range	100 ~ 24000 Hz
Frequency Response	70 ~ 25000 Hz
SPL IEC268-5, 1W/1m	89,9 dB
SPL EN54-24, Pmax/4m	92,8 dB
Power	60/30/15 W (8ohm)



## PRO 60-130T/ PLUS WHITE-EN54

### Mounting Instruction

1. Mount the inclination-adjustable stainless steel bracket on the ceiling.
2. Attach the speaker with the screws to the stainless steel bracket.
3. Remove the rear cover of the loudspeaker.
4. Guide the loudspeaker cable through the cable gland.
5. Connect the loudspeaker cable to the rear terminal.  
Make power adjustments at the rear of the speaker as needed.
6. Replace the rear cover.



CE-Symbol according to 93/68EWG  
Measurements according to DIN IEC 268-5  
RoHS compliant (2011/65/EU)  
CPR compliance according 305/2011/EU

Loudspeaker for voice alarm systems for fire detection and fire alarm systems for buildings : EN54-24:2008  
ic audio GmbH, Boehringerstraße 14A :  
D-68307 Mannheim, Germany

TO MAKE PEOPLE LISTEN